

# Print Utility for Android Operating Environment

## Operating Environment of Print Utility for Android

Item		Description
<b>Network Protocol</b>		LPD
<b>Tested devices &amp; OS versions</b>		ASUS Nexus7 (2013) (Android™ 4.4.2) Dell Venue 8 (Intel) (Android™ 4.4.2) Google Pixel (Android™ 8.1.0) HTC Nexus9 (Android™ 7.1.1) Huawei Nexus6P (Android™ 8.1.0) LG Nexus5 (Android™ 6.0.1/6.0) Samsung Galaxy S4 (Android™ 5.0.1) Samsung Galaxy S6 (Android™ 7.0) Samsung Galaxy S6 Edge (Android™ 6.0.1) Samsung Galaxy S8 (Android™ 7.0) SONY Xperia Z3+ (Android™ 6.0.1) Xiaomi Mi 5 (Android™ 6.0.1)
<b>Supported Languages</b>		English, Chinese (Simplified / Traditional), Korean, Japanese, Thai, Vietnamese, Indonesian
<b>Features</b>		Printing from application Printing web pages Printing photos saved in the photo album Printing photos taken by the internal camera Linking with Cloud Service Hub Printing DocuWorks and PDF documents Printing from Application Working with ApeosWare Management Suite Server-less On-Demand Print Scan from scanner Linking with NFC
<b>Print settings</b>	<b>Printing photo/image/website</b>	Specify the number of copies (max 99) Paper size: A3, A4, Letter, 4 x 6" (101.6 x 152.4 mm), 2L-size (127 x 178 mm), Postcard (100 x 148 mm) Image orientation: Portrait / Landscape Output Color: On / Off 2-sided print: On / Off Pages Per Sheet: 2 Pages Up / 4 Pages Up / 8 Pages Up / 16 Pages Up / 32 Pages Up (32 Pages up only for printing from photo gallery) Stapling: Off / 1 Staple Top Left Paper tray: Automatically Select / Bypass tray Paper type: Plain / Heavyweight / Heavyweight Reload Authentication and Accounting

Item	Description
	<p>Specify the number of copies (max 99)</p> <p>Paper size: Same as Paper Size, A4, A3, A5, B4, B5, Letter, Legal, 11 x 17", Postcard (100 x 148 mm)</p> <p>Collated: On / Off</p> <p>Output Color: On / Off</p> <p>2-sided print: 1sided Print / 2sided Print / 2sided, Flip on short Edge</p> <p>Pages Per Sheet: 2 Pages Up / 4 Pages Up</p> <p>Stapling: Off / 1 Staple Top Left</p> <p>Paper tray: Automatically Select / Bypass tray</p> <p>Authentication and Accounting</p>
<b>Scanner settings</b>	<p>[Scan Size] A4 / Letter</p> <p>[Resolution] 200 dpi / 300 dpi</p> <p>[Image Type] Full Colour / Grayscale</p> <p>[File Format] JPEG / PDF / DocuWorks</p>
<b>Printer settings</b>	<p>Specifying an IP address directly <sup>*1</sup></p> <p>Searching for a printer by using Bonjour <sup>*2</sup> <sup>*3</sup></p>

\*1: An IP address and port number must have been specified on the multifunction printer or printer.

\*2: An IP address and port number must have been specified on the multifunction printer or printer, and Bonjour must be running.

\*3: Search with Bonjour is not available when accessing from the secondary Ethernet of MFD.